



Model AH-0315
Manufactured:

GID HORING LIH INDUSTRIAL CO.,LTD.

MADE IN TAIWAN

# Multi-Purpose Smoke and Heat Detector



### **Operation Theory**

Advanced Multi-Sensor is a microprocessor-based smoke detector that uses a combination of photoelectric and thermal sensing technologies. It provides early warning and an accurate analysis of alarm situation. These state-of-the- art algorithms also provide a high immunity to nuisance alarm.

#### Specification

AH-0315-2, AH-0315-3,		
AH-0315-4		
12 ~ 30V DC		
55µA		
120mA		
40mA 30mA 40mA		
Comply to UL&EN standard		
58 <b>°</b> C		
Comply to EN54, Grade 1		
-10°C ~ +55°C		
Fire-proof plastic		
102mm(Dia.) x 55mm(H)		
155g 157g 165g		
lvory		

#### Effective Alert Area

Building Height	Area Covered
Under4M	150M <sup>2</sup>
4-20M	75M <sup>2</sup>

#### Order Information

AH-0315-2	2-Wire
AH-0315-3	3-Wire With Remote Indicator
	Output
AH-0315-4	4-Wire With Relay Output

## Resettable Type Detector

This unit is designed for relay output feature with optional individual power source and it has used widely in the current market. This resettable detector does not only used for fire alarm system but also will supervise input power via optional relay output for power breakdown or wire break, fault relay contact will open when power breakdown happened and fire alarm signal will transmitted to connected system or computer terminal when detector is activate. When the alarm signal is clear and the detector will automatically back to standby status. Optional built-in buzzer could sound for warning purpose at the first stage of fire. This detector is currently used quite often in security system and is also promote to apply for communication, banking, shipping or art business and it still under development for more applications in the future.

## Specification (Resettable)

Model	AH-0315-S, AH-0315-BS,		
	AH-0315-BPS		
Alarm Current	25mA	65mA	80mA
Standby Current	125µA	125µA	15mA
Voltage Range	12V DC	12V DC	12V DC
Weight	164g	166g	171g

## Order Information (Resettable)

AH-0315-S	+ Relay Output
AH-0315-BS	+ Buzzer + Relay Output
AH-0315-BPS	+ Buzzer + Power off &
	Wire Disconnection
	Warning + Relay Output

