

# AH-00212

## Fire Alarm Control Panel



### LED Description

- FIRE : Indicates fire status
- Power : Indicates unit is in normal status
- Short C. : Indicates short-circuit
- Discon. : Indicates disconnection
- S.T. : Controls H1 & H2 for activation, light on means inactive
- Bell : Activates unit's sounder and external bell, light on means inactive
- Reset : Turns system back to initial status

### Specifications

Model	AH-00212
Power	220V AC/50Hz *Others also available
Battery Capacity	24V DC 1.2Ah
Charging Voltage, Current	26V DC 100~400mA *With auto adjustment function
Exterior Resistance	Round-trip under 50Ω
# of heat detectors connected	No limit *Except electronic-type
# of smoke detectors connected	30/zone *Horing Lih manufactured
Max. Output Current	500mA
Digital Switch	500000 Cycles Min. reliability
End of Line Resistor	10kΩ *One per zone
Material	1.2mm steel plate
Color	Ivory white *Others also available
Dimension	210mm (H) x 280mm (W) x 70mm (D)

**Agent In Thailand : U.P.TECH CORPORATION CO.,LTD**

28 Soi Rattanathibet 28 Yaek 2 Bangkrasor Muangnonthaburi  
Nonthaburi 11000 Thailand

**LINE** : 0863133492 **Tel** : 02-965-7701-6, 086-355-6781

**Email** : sales@up-t.com **Email** : admin@up-t.com

**Website** : www.alarmpthailand.com , www.firealarmonline.com

**HORING LIH INDUSTRIAL CO., LTD.**

4F., No. 18, Lane 327, Chung Shan Road, Sec. 2, Zhonghe District 235, New Taipei City, **Taiwan**

**Tel** : +886 2 22487599 **Fax** : +886 2 22407752 **Email** : export@horinglih.com **Website** : www.horinglih.com